


StarTech.com Adaptador Tarjeta FireWire PCI-Express Bajo Perfil de 2 Puertos F/W 800 y 1 Puerto F/W 400


Marca : StarTech.com

Código del producto: PEX1394B3LP

Nombre del producto : Adaptador Tarjeta FireWire PCI-Express Bajo Perfil de 2 Puertos F/W 800 y 1 Puerto F/W 400



- Dos puertos FireWire 800 de 9 pines con velocidades de transferencia de hasta 800 Mbps
 - Un puerto FireWire 400 de 6 pines con velocidades de transferencia de hasta 400 Mbps
 - Incluye soporte de instalación de perfil completo o estándar
 - Construida con un chipset PCI Express nativo y sin chip puente
 - Conector de energía interno para dispositivos FireWire de alta potencia
 - Compatible con IEEE 1394b y versiones anteriores con estándares IEEE 1394a - 2000 y 1394-1995
 - Soporta Plug and Play y Hot-Swap
- StarTech.com Adaptador Tarjeta FireWire PCI-Express Bajo Perfil 1394a/b - 1x FireWire 400 6 pines Hembra - 2x FireWire 800 9 pines Hembra



Puertos e Interfaces		Requisitos del sistema	
Interfaz de host *	PCIe	Sistemas operativos Mac soportados	Mac OS X 10.10 Yosemite, Mac OS X 10.11 El Capitan, Mac OS X 10.12 Sierra, Mac OS X 10.6 Snow Leopard, Mac OS X 10.7 Lion, Mac OS X 10.8 Mountain Lion, Mac OS X 10.9 Mavericks, Mac OS X 11.0 Big Sur, Mac OS X 12.0 Monterey, Mac OS X 13.0 Ventura
Interfaz de salida *	IEEE 1394/Firewire		
Estándar de tarjeta de expansión	PCIe 1.1		
Puertos corta fuegos (IEEE 1394)	3		
Cantidad de puertos FireWire 400	1		
Cantidad de puertos FireWire 800	2	Sistemas operativos Linux soportados	✓
Diseño		Sistemas operativos de servidor soportados	Windows Server 2003, Windows Server 2008 R2, Windows Server 2012, Windows Server 2019
Interno *	✓	Detalles técnicos	
Color del producto	Verde	Cumplimiento de la sostenibilidad	✓
Tiempo medio entre fallos	149905 h	Certificados de cumplimiento	CE, RoHS
Hot-swap	✓	Peso y dimensiones	
Características		Ancho	58 mm
Circuito integrado	Texas Instruments - XIO2213B	Profundidad	90 mm
Rango de transferencia de datos (máx.)	0.8 Gbit/s	Altura	20 mm
Conectar y usar (Plug and Play)	✓	Peso	43 g
Condiciones ambientales		Empaquetado de datos	
Intervalo de temperatura operativa (T-T)	0 - 70 °C	Cables incluidos	FireWire
Intervalo de temperatura de almacenaje	-20 - 90 °C	Soportes de montaje incluidos	✓
Intervalo de humedad relativa para funcionamiento	0 - 90%	Manual	✓
		Ancho del paquete	175 mm
		Largo del paquete	144 mm
		Alto del paquete	32 mm
		Peso del paquete	200 g
		Datos de logística	
		Código de Sistema de Armonización (SA)	84733020
		Cantidad por caja principal	28 pieza(s)
		Largo de la caja principal	331 mm

Requisitos del sistema	Datos de logística		
Sistemas operativos Windows soportados	Windows 10 Education, Windows 10 Education x64, Windows 10 Enterprise, Windows 10 Enterprise x64, Windows 10 Home, Windows 10 Home x64, Windows 10 Pro, Windows 10 Pro x64, Windows 11, Windows 11 x64, Windows 7 Enterprise, Windows 7 Enterprise x64, Windows 7 Home Basic, Windows 7 Home Basic x64, Windows 7 Home Premium, Windows 7 Home Premium x64, Windows 7 Professional, Windows 7 Professional x64, Windows 7 Starter, Windows 7 Starter x64, Windows 7 Ultimate, Windows 7 Ultimate x64, Windows 8, Windows 8 Enterprise, Windows 8 Enterprise x64, Windows 8 Pro, Windows 8 Pro x64, Windows 8 x64, Windows 8.1, Windows 8.1 Enterprise, Windows 8.1 Enterprise x64, Windows 8.1 Pro, Windows 8.1 Pro x64, Windows 8.1 x64, Windows Vista Business, Windows Vista Business x64, Windows Vista Enterprise, Windows Vista Enterprise x64, Windows Vista Home Basic, Windows Vista Home Basic x64, Windows Vista Home Premium, Windows Vista Home Premium x64, Windows Vista Ultimate, Windows Vista Ultimate x64, Windows XP Home, Windows XP Home x64, Windows XP Professional, Windows XP Professional x64	Longitud de la caja principal	504 mm
		Alto de la caja principal	237 mm



0065030837897



065030837897



5052584238794

Disclaimer. The information published here (the "Information") is based on sources that can be considered reliable, typically the manufacturer, but this Information is provided "AS IS" and without guarantee of correctness or completeness. The Information is only indicative and can be changed at any time without notification. No rights can be based on the Information. Suppliers or aggregators of this Information do not accept any liability with regard to the content of (web)pages and other documents, including its Information. The publisher of the Information can not be held liable for the content of 3rd party websites that are linking this Information or are linked to from this Information. You as the User of the Information are solely responsible for the choice and usage of this Information. You are not entitled to transfer, copy or otherwise multiply or distribute the Information. You are obliged to follow the directions of the copyright owner(s) with regard to the use of the Information. Exclusively Dutch law is applicable. With regard to price and stock data on the site, the publisher followed a number of starting points, which are not necessarily relevant for your private or business circumstances. Therefore, the price and stock data are only indicative and are subject to changes. You are personally responsible for the way you use and apply this information. As a user of the Information or sites or documents in which this Information is included, you will adhere to standard fair use including avoidance of spamming, ripping, intellectual-property violations, privacy violations, and any other illegal activity.