


ASUS P5K-VM motherboard LGA 775 (Socket T) Micro ATX

ბრენდი : ASUS

პროდუქტის კოდი: P5K-VM

პროდუქტის დასახელება : P5K-VM

ASUS P5K-VM. პროცესორის მწარმოებელი: Intel, პროცესორის ბუდე: LGA 775 (Socket T). მაქსიმალური შიდა მეხსიერება: 8 გბ, ECC compatibility: შეცდომების კორექტირების კოდის გარეშე. გრაფიკული ადაპტერის მაქსიმალური მეხსიერება: 256 მბ, გრაფიკული ადაპტერი: GMA 3100. LAN-ის რეგულატორი: Marvell 88E8056, ქსელის თვისებები: Gigabit Ethernet. დედა-პლატის ფორმ-ფაქტორი: Micro ATX, Audio chip: Realtek ALC883, Power source type: ATX



| Processor | | Rear panel I/O ports | |
|----------------------------------|--------------------|-------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Processor manufacturer * | Intel | VGA (D-Sub) ports quantity * | 1 |
| Processor socket * | LGA 775 (Socket T) | Parallel ports quantity | 1 |
| Maximum number of SMP processors | 1 | Network | |
| Memory | | LAN controller | Marvell 88E8056 |
| Number of memory slots * | 4 | Networking features | Gigabit Ethernet |
| ECC compatibility | Non-ECC | Features | |
| Maximum internal memory * | 8 GB | Audio chip | Realtek ALC883 |
| Graphics | | Motherboard form factor * | micro ATX |
| Maximum graphics card memory | 256 MB | Power source type | ATX |
| Graphics card | GMA 3100 | Overclocking features | SFS ASUS C.P.R. PCI Express |
| Internal I/O | | Expansion slots | |
| USB 2.0 connectors * | 6 | Expansion slots | 1 x PCI-E x16 1 x PCI-E x4 2 x PCI |
| Number of SATA connectors | 4 | BIOS | |
| S/PDIF out connector | ✓ | BIOS memory size | 64 Mbit |
| Front panel audio connector | ✓ | Weight & dimensions | |
| ATX Power connector (24-pin) | ✓ | Width | 244 mm |
| Number of EATX power connectors | 1 | Depth | 244 mm |
| CPU fan connector | ✓ | Packaging content | |
| Number of chassis fan connectors | 1 | Bundled software | Drivers ASUS PC Probe II ASUS Update |
| Chassis intrusion connector | ✓ | Other features | |
| Rear panel I/O ports | | Controller 2nd interface type | UltraDMA 100/66/33 |
| USB 2.0 ports quantity * | 6 | Controller interface type | Serial ATA |
| Ethernet LAN (RJ-45) ports * | 1 | Floppy disk drive connector | ✓ |
| PS/2 ports quantity | 1 | Manageability features | WfM 2.0, DMI 2.0, WOL by PME, WOR by PME, PXE |
| Firewire (IEEE 1394) ports | 1 | Special features | ASUS AI Lifestyle Features: - AP Trigger. - ASUS AI Gear2. - ASUS AI Nap. - ASUS Q-Fan. ASUS Crystal Sound: - ASUS Noise Filter. ASUS EZ DIY: - ASUS Q-Connector. - ASUS CrashFree BIOS 3. - ASUS EZ Flash 2. |

Disclaimer. The information published here (the "Information") is based on sources that can be considered reliable, typically the manufacturer, but this Information is provided "AS IS" and without guarantee of correctness or completeness. The Information is only indicative and can be changed at any time without notification. No rights can be based on the Information. Suppliers or aggregators of this Information do not accept any liability with regard to the content of (web)pages and other documents, including its Information. The publisher of the Information can not be held liable for the content of 3rd party websites that are linking this Information or are linked to from this Information. You as the User of the Information are solely responsible for the choice and usage of this Information. You are not entitled to transfer, copy or otherwise multiply or distribute the Information. You are obliged to follow the directions of the copyright owner(s) with regard to the use of the Information. Exclusively Dutch law is applicable. With regard to price and stock data on the site, the publisher followed a number of starting points, which are not necessarily relevant for your private or business circumstances. Therefore, the price and stock data are only indicative and are subject to changes. You are personally responsible for the way you use and apply this information. As a user of the Information or sites or documents in which this Information is included, you will adhere to standard fair use including avoidance of spamming, ripping, intellectual-property violations, privacy violations, and any other illegal activity.

Publication date: 14-MAY-2025. Prints or copies of Information are only valid on the printed Publication date