



APC Smart-UPS SMT2200RMI2UNC - 8x C13, 1x C19, USB, rack mountable, NMC, 2200VA



Merk : APC

Artikelcode: SMT2200RMI2UNC

Productnaam : Smart-UPS SMT2200RMI2UNC - 8x C13, 1x C19, USB, rack mountable, NMC, 2200VA

APC Smart-UPS SMT2200RMI2UNC - 8x C13, 1x C19, USB, rack mountable, NMC, 2200VA
APC Smart-UPS SMT2200RMI2UNC - 8x C13, 1x C19, USB, rack mountable, NMC, 2200VA. UPS-topologie: Line-interactive, Output power capacity: 2,2 kVA, Uitgangsvermogen: 1980 W. Stopcontacttypes: C20 stekker, Stekker: C20 stekker, Aantal AC uitgangen: 9 AC-uitgang(en). Batterijtechnologie: Sealed Lead Acid (VRLA), Batterij capaciteit: 509 Ah, Accu/Batterij oplaadtijd: 5 uur. Vormfactor: Rackmontage, Kleur van het product: Zwart, Rackcapaciteit: 2U. Breedte: 480 mm, Diepte: 683 mm, Hoogte: 86 mm



Kenmerken		Design	
UPS-topologie *	Line-interactive	Vormfactor *	Rackmontage
Output power capacity *	2,2 kVA	Rackcapaciteit	2U
Uitgangsvermogen *	1980 W	Kleur van het product *	Zwart
Golfvorm *	Sinus	Type beeldscherm	LCD
Ingang operation voltage (min) *	151 V	LED-indicatoren	✓
Ingang operation voltage (max) *	302 V	Certificering	CE, EAC, EN/IEC 62040-1, EN/IEC 62040-2, GS Mark, IRAM, RCM, VDE, WEEE
Frequentie *	50/60 Hz		
Uitgang operation voltage (min)	220 V		
Uitgang operation voltage (max)	240 V		
Output frequentie	50/60 Hz		
Surge energy rating	375 J		
Responstijd	4 ms		
Emergency Power Off (EPO)	0		
Geluidsniveau	55 dB		
Spanningsbeveiliging	✓		
Geluidsalarm(en)	✓		
Web-gebaseerd management	✓		
Hoorbare alarmstanden	Batterijvervanging		
Auto-herstart	✓		
Poorten & interfaces		Eisen aan de omgeving	
Stopcontacttypes	C20 stekker	Bedrijfstemperatuur (T-T)	0 - 40 °C
Stekker	C20 stekker	Temperatuur bij opslag	-15 - 45 °C
Aantal AC uitgangen	9 AC-uitgang(en)	Relatieve vochtigheid in bedrijf (V-V)	0 - 95 procent
Aantal USB 2.0-poorten	1	Luchtvochtigheid bij opslag	0 - 95 procent
Aantal Ethernet LAN (RJ-45)-poorten	1	Hoogte, in bedrijf	0 - 3000 m
		Hoogte bij opslag	0 - 15000 m
Accu/Batterij		Technische details	
Batterijtechnologie	Sealed Lead Acid (VRLA)	Duurzaamheidscertificaten	Green Premium
Batterij capaciteit	509 Ah	Certificaten van naleving	RoHS
Accu/Batterij oplaadtijd	5 uur		
Hot-swap batterij	✓		
Automatische batterij test	✓		
Koude start	✓		
		Gewicht en omvang	
		Breedte	480 mm
		Diepte	683 mm
		Hoogte	86 mm
		Gewicht	42,2 kg
		Breedte verpakking	600 mm
		Diepte verpakking	980 mm
		Hoogte verpakking	254 mm
		Gewicht verpakking	49,6 kg
		Verpakking	
		Rekbevestigingspakket	✓
		Meegeleverde kabels	Stroomingangskabel, USB-kabel
		Snelle installatiehandleiding	✓
		Ondersteunings-cd	✓
		Logistieke gegevens	
		Producten per pallet	8 stuk(s)
		Code geharmoniseerd systeem (HS)	85078000
		Overige specificaties	
		Spanning	230 V



0731304327691



731304327691

Disclaimer. The information published here (the "Information") is based on sources that can be considered reliable, typically the manufacturer, but this Information is provided "AS IS" and without guarantee of correctness or completeness. The Information is only indicative and can be changed at any time without notification. No rights can be based on the Information. Suppliers or aggregators of this Information do not accept any liability with regard to the content of (web)pages and other documents, including its Information. The publisher of the Information can not be held liable for the content of 3rd party websites that are linking this Information or are linked to from this Information. You as the User of the Information are solely responsible for the choice and usage of this Information. You are not entitled to transfer, copy or otherwise multiply or distribute the Information. You are obliged to follow the directions of the copyright owner(s) with regard to the use of the Information. Exclusively Dutch law is applicable. With regard to price and stock data on the site, the publisher followed a number of starting points, which are not necessarily relevant for your private or business circumstances. Therefore, the price and stock data are only indicative and are subject to changes. You are personally responsible for the way you use and apply this information. As a user of the Information or sites or documents in which this Information is included, you will adhere to standard fair use including avoidance of spamming, ripping, intellectual-property violations, privacy violations, and any other illegal activity.