


MSI A520M-A PRO moederbord AMD A520 Socket AM4 micro ATX

Merk : MSI

Artikelcode: A520M-A PRO

Productnaam : A520M-A PRO

MSI A520M-A PRO. Processorfabrikant: AMD, Processor socket: Socket AM4, Compatibele processoren: 3rd Generation AMD Ryzen™ 3, 3rd Generation AMD Ryzen 5, 3rd Generation AMD Ryzen™ 7, 3rd....
Ondersteunde geheugen types: DDR4-SDRAM, Maximum intern geheugen: 64 GB, Geheugen slots type: DIMM. Ondersteunde opslagstationinterfaces: PCI Express 3.0, SATA, Ondersteunde types opslag-drives: HDD & SSD, Soorten RAID: 0, 1, 10. Maximum resolutie: 4096 x 2160 Pixels. Ethernet interface type: Gigabit Ethernet, LAN controller: Realtek RTL8111H



Processor		Interne aansluitingen	
Processorfabrikant *	AMD	Chassis intrusion aansluiting	✓
Processor socket *	Socket AM4	Aansluitingen achterzijde	
Compatibele processoren *	3rd Generation AMD Ryzen™ 3, 3rd Generation AMD Ryzen 5, 3rd Generation AMD Ryzen™ 7, 3rd Generation AMD Ryzen™ 9	Aantal USB 2.0-poorten *	2
		Aantal poorten USB 3.2 Gen 1 (3.1 Gen 1) Type A *	4
Max. aantal SMP-processoren	1	Aantal Ethernet LAN (RJ-45)-poorten *	1
Geheugen		Aantal HDMI-poorten *	1
Ondersteunde geheugen types *	DDR4-SDRAM	DVI-D poorten *	1
Aantal geheugenslots *	2	Hoofdtelefoonuitgangen	1
Geheugen slots type	DIMM	Microfoon, line-in ingang	✓
Geheugen kanaal	Dubbelkanaals	Netwerk	
ECC	✓	Ethernet LAN	✓
Non-ECC	✓	Ethernet interface type	Gigabit Ethernet
Supported memory clock speeds	1866,2133,2400,2667,2800,2933,3000,3066,3200,3466,3600,3733,3866,4000,4133,4266,4400,4600 MHz	LAN controller	Realtek RTL8111H
Maximum intern geheugen *	64 GB	Wifi *	✗
Niet gebufferd geheugen	✓	Kenmerken	
Opslag-controllers		Chipset moederbord *	AMD A520
Ondersteunde types opslag-drives	HDD & SSD	Audiochip	Realtek ALC892
Ondersteunde opslagstationinterfaces *	PCI Express 3.0, SATA	Audio-uitgangskanalen *	7.1 kanalen
Maximum aantal HDD's per behuizing	5	Kleur van het product	Zwart
RAID support	✓	Component voor *	PC
Soorten RAID	0, 1, 10	Moederbord form factor *	micro ATX
Grafisch		Moederbord chipset familie *	AMD
Ingebouwde grafische adapter	✗	Aantal montagegaten	8
Maximum resolutie	4096 x 2160 Pixels	Uitbreidingsmodules	
Aantal displays ondersteund	2	PCI Express x1 (Gen 3.x) slots	1
Interne aansluitingen		PCI Express x16 (Gen 3.x) slots	1
USB 2.0 aansluitingen *	2	Aantal M.2 (M) slots	1
USB 3.2 Gen 1 (3.1 Gen 1)-aansluitingen *	1	Logistieke gegevens	
Aantal SATA III connectors *	4	Code geharmoniseerd systeem (HS)	84733020
Aansluiting voor audiopaneel aan voorzijde	✓	Gewicht en omvang	
Voorpaneel-connector	✓	Breedte	236 mm
ATX Power connector (24-pin)	✓	Diepte	200 mm
Aansluiting voor CPU koeler	✓		
Aansluitingen voor behuizingsventilatoren	2		

Gewicht en omvang

Hoogte 60 mm

Overige specificaties

Gewicht 698 g



4719072749927



0824142224007



824142224007

Disclaimer. The information published here (the "Information") is based on sources that can be considered reliable, typically the manufacturer, but this Information is provided "AS IS" and without guarantee of correctness or completeness. The Information is only indicative and can be changed at any time without notification. No rights can be based on the Information. Suppliers or aggregators of this Information do not accept any liability with regard to the content of (web)pages and other documents, including its Information. The publisher of the Information can not be held liable for the content of 3rd party websites that are linking this Information or are linked to from this Information. You as the User of the Information are solely responsible for the choice and usage of this Information. You are not entitled to transfer, copy or otherwise multiply or distribute the Information. You are obliged to follow the directions of the copyright owner(s) with regard to the use of the Information. Exclusively Dutch law is applicable. With regard to price and stock data on the site, the publisher followed a number of starting points, which are not necessarily relevant for your private or business circumstances. Therefore, the price and stock data are only indicative and are subject to changes. You are personally responsible for the way you use and apply this information. As a user of the Information or sites or documents in which this Information is included, you will adhere to standard fair use including avoidance of spamming, ripping, intellectual-property violations, privacy violations, and any other illegal activity.